

LIGHTING POINT SOLUTION

AUXILIARY RELAY


The Auxiliary Relay is the ideal solution for controlling your Christmas lighting and other illuminated decorations installed on luminaires equipped with a BH Node.

Installed at the base of the pole or directly inside the lantern, it can be programmed via the Luce supervision platform (scenarios and schedules) and ensures the automatic shutdown of festive lighting powered by the public network.

This prevents decorations from staying on all night unnecessarily, ensuring both energy savings and enhanced public spaces.



> BH Node accessory



COMMERCIAL REFERENCE
> L-BHNODE-RELAIS-AUX : relay housing providing, among other things, the E-Lum functionality to a BH Node.

◆ TECHNICAL DATA

Coil voltage: 24 VDC

Rated voltage: 230 VAC

Rated current: 8 A

Breaking capacity: up to 2000 VA

Dielectric strength coil-contact: 5000 V RMS

Lifetime: > 30 million switching operations

Operating temperature: -20 °C / +85 °C

Protection rating: Class II, reinforced insulation

Terminal block: max. 2 × 2.5 mm²

Compliance: RoHS / REACH

Dimensions: 77 mm × 69 mm × 15.8 mm

Weight: 54 g

